



1 **EC TYPE-EXAMINATION CERTIFICATE**

2 Equipment intended for use in Potentially Explosive Atmospheres Directive 94/9/EC

3 Certificate Number: Sira 05ATEX2084X

4 Equipment: IS-mA1 Sounder, IS-mB1 Beacon & IS-mC1 Combined Sounder/Beacon

5 Applicant: European Safety Systems Limited

6 Address: Impress House
Mansell Road
Acton
London
W3 7QH
UK

7 This equipment and any acceptable variation thereto is specified in the schedule to this certificate and the documents therein referred to.

8 Sira Certification Service, notified body number 0518 in accordance with Article 9 of Directive 94/9/EC of 23 March 1994, certifies that this equipment has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of equipment intended for use in potentially explosive atmospheres given in Annex II to the Directive.

The examination and test results are recorded in confidential report number R52A13291A.

9 Compliance with the Essential Health and Safety Requirements, with the exception of those listed in the schedule to this certificate, has been assured by compliance with the following documents:

EN 50014: 1997 + A1 and A2

EN 50020: 2002

EN 50284: 1999

10 If the sign 'X' is placed after the certificate number, it indicates that the equipment is subject to special conditions for safe use specified in the schedule to this certificate.

11 This EC type-examination certificate relates only to the design and construction of the specified equipment. If applicable, further requirements of this Directive apply to the manufacture and supply of this equipment.

12 The marking of the equipment shall include the following:



II 1G

EEx ia IIC T4 (-40°C ≤ Ta ≤ +60°C)

Project Number 52A13291
Date 4 August 2005
C. Index 15

C Ellaby
Certification Officer

This certificate and its schedules may only be reproduced in its entirety and without change



SCHEDULE

EC TYPE-EXAMINATION CERTIFICATE

Sira 05ATEX2084X

13 DESCRIPTION OF EQUIPMENT

The **IS-mA1 Sounder** is designed to provide an audible warning when activated. It consists of the following mounted in an IP 65, flame retardant, ABS enclosure:

- Sounder printed circuit board assembly
- Inductive sounder transducer

External connections are made to terminals mounted on the sounder printed circuit board via cable entry devices mounted in the wall of the enclosure. The parameters for the IS-mA1 Sounder are as follows:

Terminals	Parameters				
	U _i	I _i	P _i	C _i	L _i
Terminal + w.r.t. Terminal -	28 V	93 mA	660 mW	0	0
Terminals S2 and S3 w.r.t. Terminal -	28 V	0	-	-	-

The **IS-mB1 Beacon** is designed to provide a flashing warning when activated. It consists the following mounted inside an IP 65, flame retardant, ABS enclosure that is fitted with a transparent polycarbonate 'lens':

- Beacon main printed circuit board assembly
- Beacon LED printed circuit board assembly

External connections are made to terminals mounted on the beacon main printed circuit board via cable entry devices mounted in the walls of the enclosure. The parameters for the IS-mB1 Beacon are as follows:

Terminals	Parameters				
	U _i	I _i	P _i	C _i	L _i
Terminal + w.r.t. Terminal -	28 V	93 mA	660 mW	0	0

The **IS-mC1 Combined Sounder/Beacon** is designed to provide an audible and a flashing warning when activated. It consists of the following mounted inside an IP 65, flame retardant, ABS enclosure that is fitted with a transparent polycarbonate 'lens':

- Sounder printed circuit board assembly
- Inductive sounder transducer
- Beacon main printed circuit board assembly
- Beacon LED printed circuit board assembly

External connections are made to terminals mounted on the sounder printed circuit board assembly and the beacon main printed circuit board assembly via cable entry devices mounted in the walls of the enclosure. The IS-mC1 Combined Sounder/Beacon may be supplied with internal wiring connections between Sounder Terminals + / - and Beacon Terminals + / -, alternatively these connections may be fitted by the user/installer. The parameters for the IS-mC1 Combined Sounder/Beacon are as follows:

	Terminals	Parameters				
		U _i	I _i	P _i	C _i	L _i
Without internal connections:	Sounder Terminals + w.r.t. Sounder Terminals -	28 V	93 mA	660 mW	0	0
	Sounder Terminals S2 & S3 w.r.t. Sounder Terminals -	28 V	0	-	-	-
	Beacon Terminal + w.r.t. Beacon Terminal -	28V	93 mA	660 mW	0	0
With internal connections	Sounder Terminal + w.r.t. Sounder Terminal -	28 V	93 mA	660 mW	0	0
	Sounder Terminals S2 & S3 w.r.t. Sounder Terminals -	28 V	0	-	-	-

Date 4 August 2005

This certificate and its schedules may only be reproduced in its entirety and without change

Sira Certification Service

Rake Lane, Eccleston, Chester, CH4 9JN, England
 Tel: +44 (0) 1244 670900 Fax: +44 (0) 1244 681330
 Email: exhaszard@sira.co.uk

Sira Certification Service is a service of Sira Test & Certification Ltd



SCHEDULE

EC TYPE-EXAMINATION CERTIFICATE

Sira 05ATEX2084X

14 DESCRIPTIVE DOCUMENTS

14.1	Drawing No.	Sheet	Rev.	Date	Description
	CD 5011	1 of 1	A	09 May 05	Circuit Diagram - Sounder Board
	CD 5012	1 of 1	A	09 May 05	Circuit Diagram - Beacon Board
	D 5014	1 of 1	A	03 Jun 05	Certification Label - Sounder
	D 5015	1 of 1	A	03 Jun 05	Certification Label - Beacon
	D 5016	1 of 1	A	03 Jun 05	Certification Label - Combined Sounder / Beacon
	D 5017	1 of 1	A	01 Aug 05	General Assembly - Sounder
	D 5018	1 of 1	A	03 Jun 05	General Assembly - Beacon
	D 5019	1 of 1	A	01 Aug 05	General Assembly - Combined Sounder / Beacon
	D 5021	1 of 1	A	24-Jun-05	PCB Assembly - Sounder
	PL 5021	1 of 1	A	03 Jun 05	Parts List - Sounder PCB
	D 5022	1 of 1	A	24 Jun 05	PCB Assembly - Beacon
	PL 5022	1 of 1	A	03 Jun 05	Parts List - Beacon PCB

14.2 Report number R52A13291A

15 SPECIAL CONDITIONS FOR SAFE USE (denoted by X after the certificate number)

15.1 Conditions for IS-mA1 Sounder

- The equipment has an ingress protection rating of IP65. However, if it has been supplied without cable entry devices, then the user shall ensure that the devices that are fitted will provide an ingress protection that is appropriate to the environment in which it is installed i.e. IP20 or better. If only one of the two cable entries are used, then the unused entry 'knockout' shall be left intact or fitted with a blanking device that ensures ingress protection appropriate to the environment in which it is installed i.e. IP20 or better.
- The equipment shall not be directly installed in any process where its enclosure might be electrostatically charged by the rapid flow of a non-conductive media.
- The equipment shall only be supplied via Terminals + w.r.t. Terminals - from a barrier having a maximum open circuit voltage U_0 that is $\leq 28V$ and a maximum short circuit current I_0 that is $\leq 93mA$, where I_0 is resistively limited. The barrier shall be ATEX certified by a notified body.

15.2 Conditions for IS-mB1 Beacon

- The equipment has an ingress protection rating of IP65. However, if it has been supplied without cable entry devices, then the user shall ensure that the devices that are fitted will provide an ingress protection that is appropriate to the environment in which it is installed i.e. IP20 or better. If only one of the two cable entries are used, then the unused entry 'knockout' shall be left intact or fitted with a blanking device that ensures ingress protection appropriate to the environment in which it is installed i.e. IP20 or better.
- The equipment shall not be directly installed in any process where its enclosure might be electrostatically charged by the rapid flow of a non-conductive media.

Date 4 August 2005

This certificate and its schedules may only be reproduced in its entirety and without change



SCHEDULE

EC TYPE-EXAMINATION CERTIFICATE

Sira 05ATEX2084X

15.3 Conditions IS-mC1 Combined Sounder/Beacon

- The equipment has an ingress protection rating of IP65. However, if it has been supplied without cable entry devices, then the user shall ensure that the devices that are fitted will provide an ingress protection that is appropriate to the environment in which it is installed i.e. IP20 or better. If only one of the two cable entries are used, then the unused entry 'knockout' shall be left intact or fitted with a blanking device that ensures ingress protection appropriate to the environment in which it is installed i.e. IP20 or better.
- The equipment shall not be directly installed in any process where its enclosure might be electrostatically charged by the rapid flow of a non-conductive media.
- The equipment shall only be supplied via Sounder Terminals + w.r.t. Sounder Terminals – from a barrier having a maximum open circuit voltage U_o that is $\leq 28V$ and a maximum short circuit current I_o that is $\leq 93mA$, where I_o is resistively limited. The barrier shall be ATEX certified by a notified body.
- If not already fitted, optional internal wiring connections between Sounder Terminals + / - and Beacon Terminals + / - may be fitted by the user. The wiring used for such connections shall have a minimum radial thickness of insulation of 0.5mm.

16 ESSENTIAL HEALTH AND SAFETY REQUIREMENTS OF ANNEX II (EHSRs)

The relevant EHSRs that are not addressed by the standards listed in this certificate have been identified and individually assessed in report number R52A13291A.

17 CONDITIONS OF CERTIFICATION

- 17.1 The use of this certificate is subject to the Regulations Applicable to Holders of Sira Certificates.
- 17.2 Holders of EC type-examination certificates are required to comply with the production control requirements defined in Article 8 of directive 94/9/EC.

Date 4 August 2005

This certificate and its schedules may only be reproduced in its entirety and without change